

Generating Set Range Guide

2.8 - 70 kVA

50 Hz 1500 r/pm



POWERED BY LISTER PETER ENGINES

Model	Open	A3	A5	A6	A13	A20	W7	W12	W16	W22	W25	W30	W35	W50	W70
	Acoustic	A3(A)	A5(A)	A6(A)	A13(A)	A20(A)	W7(A)	W12(A)	W16(A)	W22(A)	W25(A)	W30(A)	W35(A)	W50(A)	W70(A)
Engine	Lister Petter	LP 2.8*	LP 4.5*	TR1	TR2	TR3	LPW2	LPW3	LPW4	LPWT4	SIGMA 20	SIGMA 25	SIGMA 30	GAMMA 50	GAMMA 70
Single Phase	Prime (kVA)	2.8	4.5	4.1	8.6	14.0	5.6	8.7	12.2	-	-	-	-	-	-
	Standby (kVA)	3.1	5.0	4.5	9.4	15.4	6.1	9.5	13.5	-	-	-	-	-	-
Three Phase	Prime (kVA)	-	-	5.3	11.2	18.1	7.0	10.9	15.0	20.0	20.0	25.0	30.0	45.0	63.0
	Standby (kVA)	-	-	5.9	12.3	19.5	7.6	12.0	16.5	22.0	22.0	27.5	33.0	49.5	69.3

* These engines are 3000 r/min

82 - 690 kVA

50 Hz 1500 r/pm



POWERED BY VOLVO ENGINES

Model	Open	W80	W90	W110	W140	W165	W200	W220	W275	W300	W330
	Acoustic	W80(A)	W90(A)	W110(A)	W140(A)	W165(A)	W200(A)	W220(A)	W275(A)	W300(A)	W330(A)
Engine	Volvo	TD 520 GE	TD 520 GE	TAD 531 GE	TAD 532 GE	TAD 731 GE	TAD 732 GE	TAD 733 GE	TAD 734 GE	TAD 940 GE	TAD 941 GE
Three Phase	Prime (kVA)	75.0	85.0	100.0	125.0	150.0	185.0	200.0	250.0	275.0	300.0
	Standby (kVA)	82.5	93.5	110.0	137.5	165.0	203.5	220.0	275.0	302.5	330.0

Model	Open	W390	W420	W440	W500	W550	W620	W690			
	Acoustic	W390(A)	W420(A)	W440(A)	W500(A)	W550(A)	W620(A)	W690(A)			
Engine	Volvo	TAD 1240 GE	TAD 1241 GE	TAD 1242 GE	TAD 1640 GE	TAD 1641 GE	TAD 1642 GE	TWD 1643 GE			
Three Phase	Prime (kVA)	350.0	375.0	400.0	450.0	500.0	560.0	625.0			
	Standby (kVA)	385.0	412.5	440.0	495.0	550.0	616.0	687.5			

A=Air Cooled W=Water Cooled



Hawk-Pack (A) - 2.8-5.0 kVA



Acoustic Set (A & W) - 5.9-43.5 kVA



Open Set (W) - 5.9-43.5 kVA



Acoustic Set (W) - 20.0-33.0 kVA



Acoustic Set (W) - 75-300 kVA



Acoustic Set (W) - 350-625 kVA

HAWKPOWER (Pty) Ltd. Directech Industrial Park, Corner Homestead & Orleans Roads, Kya-Sand, Randburg, South Africa

T: +27 11 708 2202 **F:** +27 11 708 2217 **W:** www.hawkpowergenerators.com

For sales enquiries please email: sales@hawkpowergenerators.com

For technical enquiries please email: technical@hawkpowergenerators.com

© Copyright Hawkpower, May 2009. The information in this literature is accurate at time of publication. Hawkpower reserve the right to amend specifications and information without notice and without obligation or liability.